

# TIGER G2



TG-T9-1 / 100-001-595-96

|                                   |                                      |
|-----------------------------------|--------------------------------------|
| <b>Article no.</b>                | TG-T9-1 / 100-001-595-96             |
| <b>Frequency</b>                  | 433 MHz , 69 channels                |
| <b>Duplex</b>                     | Yes                                  |
| <b>Mod.type</b>                   | FM-Modulation, narrow band           |
| <b>Code comb.</b>                 | 4.200.000.000                        |
| <b>Radio type</b>                 | Low IF topology                      |
| <b>Output</b>                     | 10 mW (by 50 ohm)                    |
| <b>Buttons</b>                    | 8 x 2 -step buttons                  |
| <b>No. of batteries</b>           | 1                                    |
| <b>Battery</b>                    | Re-chargeable                        |
| <b>Type of batteries</b>          | li-ion                               |
| <b>Weight</b>                     | 295 gr /~ 0.7 lb                     |
| <b>Dimensions</b>                 | 76 x 160 x 37 mm /~ 3 x 6.3 x 1.5 In |
| <b>Protection</b>                 | IP66                                 |
| <b>Temperature</b>                | -20 to +55 C / -4 to 131 F           |
| <b>Safety level</b>               | PLe, SIL3                            |
| <b>Certifications</b>             | CE                                   |
| <b>On/off switch</b>              | Yes                                  |
| <b>RFID</b>                       | Accessory: wall tag                  |
| <b>PIN code</b>                   | 6                                    |
| <b>Op. time with cont. usage:</b> | 30 h                                 |

The product picture above is for illustrative purposes only, actual product appearance might be slightly different